
2.4GHz Directional Patch Panel Antenna

AX-106M





Remove one default antenna from the wireless device and start to assemble!

SparkLAN antenna AX-106M is an indoor direction antenna that enabled you to increase the performance of your IEEE802.11b wireless LAN. You can use the antenna in combination with the IEEE 802.11b Wireless devices.



Device connector (RPSMA-jack)






Horizontal coverage

Vertical coverage

Frequency band	2.4-2.5GHz
Antenna gain	6dBi
VSWR	1.5 max
Polarization	Linear vertical
HPBW / H-plane	80Ë
HPBW / E-plane	80Ë
Impedence	50 Ohms
Dimensions HxWxD	115x76x33mm
Weight	110g without joint

Ceiling mount



Wall Mount

A CAUTION:

- 1. Always place the antenna on a flat or secure surface.
- 2. Concealing the antenna behind books, cabinets or other office equipment may affect the performance of the wireless networks.
- 3. The antenna transmission range may vary according to different enviornments or applications.

Package Contents:

- AX-106M Antenna
- With 90cm cable
- Mounting Kit
- Quick Installation Guide

Above specification change without notice / All rights belong to SparkLAN Communications, Inc.

